

# DIN Rail RTU 540CMD01

## Data sheet



## Application

The 540CMD01 is a module of the RTU540 product line consisting of a communication unit (CMU) and a galvanic isolated wide range power supply (PSM) in a metal DIN rail housing.

The essential tasks are:

- Managing and controlling of the RTU520 I/O modules via the serial I/O bus
- Reading Process events from the input modules.
- Send commands to the output modules.
- Communicating with control systems and local HMI systems via the serial interfaces (RS232) and the Ethernet 10/100BaseT interfaces.
- Communication with Sub-RTU's, IED's or multimeter devices via the interfaces (RS485) and the Ethernet interfaces.
- Managing the time base for the RTU540 product line station and synchronizing the I/O modules.
- Handling the dialog between RTU540 product line and Web-Browser via the LAN interfaces.

The unit has a battery buffered real time clock (RTC).




Figure 1: Function block diagram 540CMD01

## Characteristics

On the applied ARM cortex A8 controller AM3352 a real-time operating system is implemented. The 540CMD01 is responsible for the interface management, the event handling, the time base and the internal data base. The controller acts as master for the serial I/O bus (WRB).

System relevant configuration files are stored in the non-volatile flash memory card (removable SD-card™) in order to guarantee a valid system configuration after Power on Reset (PoR).

A battery buffered RTC is used to keep an exact time during power off state.

The communication unit provides the following interfaces:

- Communication Port 1 ... 4 (CP1 ... CP4): serial interfaces according RS232C or RS485 with RJ45 connectors.
- Ethernet interface 1 and 2 (E1 & E2): 10/100BaseT with RJ45 connector.
- USB 2.0 device interface for diagnosis and maintenance purposes.
- USB 2.0 host interface for future extensions.
- WRB I/O bus interface for local communication with the I/O-modules




Figure 2: Top side of 540CMD01 housing




Figure 3: Front side of 540CMD01 housing




Figure 4: Bottom side of 540CMD01 housing

## Technical data

In addition to the RTU500 series general technical data, the following applies:

Main Processing Unit MPU	
CPU	ARM cortex A8, AM3352 @ 800 MHz
RAM	256 MByte
Boot Flash	8 MByte
SD card	
Connector	SD card slot (push push)
Type	SD 2.0, class 2
Capacity	4 GByte
Real time clock RTC (Backup)	
Battery	Lithium 3 V DC, CR2032
Time resolution	1 sec, 1ms with timesync
Battery lifetime	> 10 years
Free running	± 50 ppm
Serial interfaces 1, 2, 3, 4	
Connector	RJ45
Type	RS232C or RS485
RS232C:	
Bit rate	200 bit/s - 38.4 kbit/s
Signal lines	GND E2/102
	TxD D1/103
	RxD D2/104
	RTS S2/105
	CTS M2/106
	DTR S1.2/108
	DCD M5/109
Level	typical: ± 6V
RS485:	
Bit rate	200 bit/s - 38.4 kbit/s
Level	typical: ± 6V
Ethernet interface E1 and E2	
Connector	RJ45
Type	IEEE 802.3, 10/100BaseT
USB interface 1	
Connector	USB Type A (for future extensions)
Type	USB 2.0 host, low and full speed (max. 12 MBit/s)

USB interface 2	
Connector	USB Type B (configuration interface)
Type	USB 2.0 device, low and full speed (max. 12 MBit/s)
Signaling by LEDs	
ERR (red)	ON: RTU in error state Flashing: RTU in warning state For more details see RTU500 series Function Description
RUN (green)	Communication module in operation
PF (red)	Failure of one of the internal voltages (24 V DC out not included)
I/O bus (green)	Transmission on to the I/O bus
T	Transmit data on serial communication ports CP
R	Receive data on serial communication ports CP
S	Ethernet communication speed: ON: 100 Mbit/s OFF: 10 Mbit/s
L	Link up on Ethernet interface E
Power supply input	
Input voltage	24 ... 125 V DC
Input tolerance range	-20%... +20%
Max. input current	2 A
Efficiency	88% @ 24 V DC
Power consumption	5.4 Watt (0.0 A @ 24 V out)
External circuit-breaker	The plus lead needs a be protected by a circuit-breaker upstream with 10 A trip current.
Reverse voltage protection	yes
Potential isolation between input and outputs	yes
Power supply output	
Total output power	30 W
24 V DC power supply output	
Voltage	24 V DC (galvanic isolated)
Tolerance	±20 %
Max. current	500 mA
Residual ripple	≤ 200 mVpp
Current supply for power supplied via WRB bus	
5 V DC (±5 %)	1.8 A

<b>Current supply for power supplied via WRB bus</b>	
±15 V DC (±10 %)	200 mA
18 V DC (±20 %)	50 mA
<b>Mechanical layout</b>	
Dimensions	204 mm x 105 mm x 70 mm (Width x Height x Depth)
Housing type	
Mounting	
Weight	ca. 940 g
<b>Immunity test</b>	
Electrostatic discharge IEC 61000-4-2	8 kV air / 6 kV contact (level 3) Performance criteria A
Radiated Radio-Frequency Electro-magnetic Field IEC 61000-4-3	10 V/m (level 3) Performance criteria A
Electrical Fast Transient / Burst IEC 61000-4-4	4 kV (level X) Performance criteria A
Surge IEC 61000-4-5	4 kV (level 4) Performance criteria A
Conducted Disturbances, induced by Radio-Frequency Fields IEC 61000-4-6	10 V (level 3) Performance criteria A
Damped oscillatory wave IEC 61000-4-18	2.5 / 1 kV (level 3) Performance criteria A
<b>Environmental conditions</b>	
Nominal operating temperature range: Start up: EN 60068-2-1, -2-2, -2-14	-25°C... 70°C -40 °C
Relative humidity EN 60068-2-30	5 ... 95 % (non condensing)
<b>Ordering information</b>	
540CMD01 R0001	1KGT037400R0001



**Note:**

The specifications, data, design or other information contained in this document (the "Brochure") - together: the "Information" - shall only be for information purposes and shall in no respect be binding. The Brochure does not claim to be exhaustive. Technical data in the Information are only approximate figures. We reserve the right at any time to make technical changes or modify the contents of this document without prior notice. The user shall be solely responsible for the use of any application example or information described within this document. The described examples and solutions are examples only and do not represent any comprehensive or complete solution. The user shall determine at its sole discretion, or as the case may be, customize, program or add value to the ABB products including software by creating solutions for the end customer and to assess whether and to what extent the products are suitable and need to be adjusted or customized.

This product is designed to be connected to and to communicate information and data via a network interface. It is the users sole responsibility to provide and continuously ensure a secure connection between the product and users or end customers network or any other network (as the case may be). The user shall establish and maintain any appropriate measures (such as but not limited to the installation of firewalls, application of authentication measures, encryption of data, installation of anti-virus programs, etc) to protect the product, the network, its system and the interface against any kind of security breaches, unauthorized access, interference, intrusion, leakage and/or theft of data or information. ABB AG is not liable for any damages and/or losses related to such security breaches, any unauthorized access, interference, intrusion, leakage and/or theft of data or information.

ABB AG shall be under no warranty whatsoever whether express or implied and assumes no responsibility for the information contained in this document or for any errors that may appear in this document. ABB AG's liability under or in connection with this Brochure or the files included within the Brochure, irrespective of the legal ground towards any person or entity, to which the Brochure has been made available, in view of any damages including costs or losses shall be excluded. In particular ABB AG shall in no event be liable for any indirect, consequential or special damages, such as – but not limited to – loss of profit, loss of production, loss of revenue, loss of data, loss of use, loss of earnings, cost of capital or cost connected with an interruption of business or operation, third party claims. The exclusion of liability shall not apply in the case of intention or gross negligence. The present declaration shall be governed by and construed in accordance with the laws of Switzerland under exclusion of its conflict of laws rules and of the Vienna Convention on the International Sale of Goods (CISG).

ABB AG reserves all rights in particular copyrights and other intellectual property rights. Any reproduction, disclosure to third parties or utilization of its contents - in whole or in part - is not permitted without the prior written consent of ABB AG.

© Copyright ABB 2016

All rights reserved